Express Mail Label No. EV375068852US

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau

(43) International Publication Date
31 July 2003 (31.07.2003)

PCT

(10) International Publication Number
WO 03/063003 A2

(51) International Patent Classification[7]: G06F 13/40

(21) International Application Number: PCT/GB03/00204

(22) International Filing Date: 20 January 2003 (20.01.2003)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
0201223.5 19 January 2002 (19.01.2002) GB
0219913.1 28 August 2002 (28.08.2002) GB

(71) Applicant *(for all designated States except US)*: INCORPORATED TECHNOLOGIES (HOLDINGS) LIMITED [GB/GB]; 1 Pavillions, Alloa, Clackmannanshire FK10 1TA (GB).

(72) Inventor; and
(75) Inventor/Applicant *(for US only)*: MCDONALD, Donald, Wilson [GB/GB]; Wrights House, West Green, Culross, Fife KY12 8JH (GB).

(74) Agent: KENNEDYS PATENT AGENCY LIMITED; Floor 5, Queens House, 29 St Vincent Place, Glasgow G1 2DT (GB).

(81) Designated States *(national)*: AE, AG, AL, AM, AT (utility model), AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ (utility model), CZ, DE (utility model), DE, DK (utility model), DK, DM, DZ, EC, EE (utility model), EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SD, SE, SG, SK (utility model), SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VN, YU, ZA, ZM, ZW.

(84) Designated States *(regional)*: ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

[Continued on next page]

(54) Title: KIOSK TECHNOLOGY KIT



(57) Abstract: A control module (10) and socket server architecture that occupies one expansion slot on a PC motherboard providing several functions and ports needed for embedding a motherboard in a kiosk application environment. The control module includes a motherboard bus connector (11), a motherboard bus to serial port bridge module (12), at least one serial port connector (13) and a processor module (16).

WO 03/063003 A2

Published:

— *without international search report and to be republished upon receipt of that report*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

4/pRT

1 **Kiosk technology kit**

2

3 This invention relates to computer systems, in
4 particular, interfacing personal computers (PCs) to
5 peripherals in a multi-media kiosk applications.
6
7 In an embedded environment such as a kiosk, a PC needs to
8 be configured and supported with additional hardware to
9 provide system reliability and robustness and multiple
10 device interfaces.
11
12 In the prior art systems are known for embedding standard
13 PC hardware within a kiosk application. Such a system is
14 provided by Coynet UK Limited that uses hardware
15 containing an embedded processor on a control circuit
16 board programmed to influence the PC in a kiosk
17 application. During initialisation of the PC, or if the
18 PC control program is not in operation, the processor
19 automatically detects potential vulnerability in the
20 system and automatically takes steps to prevent use of
21 this system until it is once more stable and secure.
22

A significant problem with this and other known prior art solutions to is the inefficient use of input/output (I/O) ports of the PC. I/O ports such as serial RS-232 ports are needed for communication with kiosk peripherals such as coin mechanisms, note readers, meters for counting, card readers and printers.

Even more ports, including RS-232 and motherboard expansion slots (e.g. PCI, Peripheral Component Interconnect) are needed for hardware used to monitor the health and security of the PC, for example, controlling the power supply and monitoring the software and hardware state of the PC. An uninterruptable power supply (UPS) is desirable for monitoring and control of power to the motherboard and this is typically monitored and controlled by the motherboard itself using an RS-232 port. A watchdog capability is useful to monitor the state of the PC and this typically requires a processor unit (e.g. a microcontroller) external to the motherboard connected to the motherboard via a RS-232 port and other connectors on the motherboard. In a kiosk system it is desirable to have digital Digital Input/Output (DIO), and this typically is achieved by using a PCI slot on the motherboard with a DIO card or by having an RS-232 port connection to a DIO device. An embedded system can be further improved with the ability to store customer specific data in non-volatile memory in order to provide security features, and this is typically achieved with the use of a PCI slot, an RS-232 port or a parallel port. Another desirable features is output to an amplifier and speaker which is typically done through a PCI slot with a sound card. Communication with other processor such as using the I^2C (Inter-IC) bus would typically use another

PCI slot the motherboard for a communications adapter card. The I²C bus is a standard two-wire serial bus used in a variety of microcontroller-based embedded applications for control, diagnostics and power management. Yet another feature possible in an embedded system is monitoring of the state of batteries connected to the uninterruptable power supply, and this could be achieved using hardware connected to another port of the PC.

It can be seen that there are not enough ports on a standard PC motherboard to supply all of the connectivity to kiosks peripherals and for all of the desirable functions listed above. The conventional approach to this problem is to provide port expansion hardware, typically occupying a PCI slot with a bank of UARTs (Universal Asynchronous Receiver/Transmitters) controlled by a microcontroller. The problem with this approach is the cost and the complexity of software event handlers needed to control all of the peripherals attached via the bank of UARTs. It is not possible with this approach to use a standard plug and play architecture for added applications on the host PC because special event handler code needs to be written at the microcontroller level or a special abstraction layer and API (Application Programming Interface) needs to developed.

It would be advantageous to provide an architecture and a control module that fulfilled all of the desirable peripheral connection needs and all of the control functions for a PC in an embedded application such as a kiosk.

It is an object of the present invention to provide a control module and architecture that occupies one expansion slot on a PC motherboard while providing a plurality of functions and ports needed for embedding a motherboard in a kiosk application environment.

According to a first aspect of the present invention, there is provided a control module comprising:

a motherboard bus connector for communication with a motherboard;

a motherboard bus to serial port bridge module;

at least one serial port connector; and

a processor module.

Preferably the control module is adapted to provide at least one peripheral control port for said motherboard.

Preferably the processor module comprises a monitoring means for monitoring the state of said motherboard.

Typically, the monitoring means further monitors the state of software running on said motherboard.

Preferably the processor module has a battery power supply separate from the PC power supply.

Preferably processor module further comprises a power supply monitoring means for monitoring the state of a power supply supplying said motherboard.

According to a second aspect of the present invention, there is provided a system comprising a motherboard and the control module in accordance with the first aspect.

Preferably the system further comprises a socket server means for providing event handlers for at least one serial port corresponding to said at least one serial port connector and operating substantially in between the application layer and the operating system layer of the software executing on the motherboard.

More preferably, the system further comprises a socket server means for providing event handlers for said at least one peripheral control port and operating substantially in between the application layer and the operating system layer of the software executing on the motherboard.

Preferably, the system further comprises a battery, a power supply and a battery management circuit wherein an electrical connection between said battery and said power supply is diverted through said battery management circuit and said battery management circuit is controlled by said processor module.

In order to provide a better understanding of the present invention, an embodiment will now be described by way of example only and with reference to the accompanying figures in which:

- Figure 1 illustrates in schematic form a control module in accordance with the present invention;

- Figure 2 illustrates in schematic form a software architecture in accordance with the present invention; and

- Figure 3 illustrates in schematic form a system including a control module, a peripheral interface module and peripherals in accordance with the present invention.
- Figure 4 illustrates in schematic form a power supply system in accordance with the present invention.

The invention is a card for connecting to a PC motherboard that functions to provide serial port expansion, digital I/O port (DIO) expansion and control functions for a PC in an embedded environment.

With reference to Figure 1, the control module 10 is shown comprising a PCI connector 11, a PCI/RS-232 bridge chip 12 comprising four UARTs with output to a single multifunction connector 13 that includes three RS-232 ports 14 and two eight-bit DIO ports 15.

One RS-232 port from the bridge chip is connected to a processor module which is a microcontroller unit 16 that includes FLASH EEPROM memory 17 and boot loader ROM 18.

A Dallas iButton 19 from Dallas Semiconductor Corp. is provided for measuring temperature, providing further non-volatile memory (EEPROM), a real time clock and a unique serial number. The serial number is used for provision of security features, including software licence verification, thus acting as a 'dongle'.

A power supply controller circuit 110 and connection 111 to the host motherboard's power supply unit is provided.

The microcontroller has its own back-up battery supply 115. An amplifier driver 112 for a speaker 113 and an I^2C Bus interface 114 are also provided.

A motherboard interface 116 has a connector 117 for a cable to the motherboard reset and power on pins.

The microcontroller performs a number of key tasks and communicates with the host motherboard via the PCI slot. The full utilisation of the microcontroller requires installation of a socket server layer (described below with reference to Figure 2) and a power control API on the host system.

The microcontroller provides management of the power system including the UPS and provides automatic shutdown of the system after a preset period of AC (alternating current) power loss. This is set to 3 minutes normally. In addition, some motherboard / operating system combinations can behave differently with respect to AC power loss and restart conditions. The microcontroller is programmed to automatically restart the system after power restoration and deal with any issues related to ACPM/BIOS (Advanced Configuration and Power Management / Basic Input/Output System).

If the host system hangs, there may be now no way to recover the system other than a full hardware reboot. The microcontroller can detect when the system hangs and automatically reboot. This can be programmed to cycle a number of times to try to recover the system. Reboot status is held within the microcontroller or iButton EEPROM.

The microcontroller or iButton EEPROM stores factory set-up data to aid situations where remote management is being used or for a quick status inspection in the field.

A 2x16 character LCD (Liquid Crystal Display) can be fitted to the control module to display system information. Factory device identity and local error codes can be displayed to provide assistance in diagnosing field problems.

The microcontroller is connected to the multifunction connector to provide a number of DIO ports for control applications. The DIO control lines are configured as inputs and outputs for system interfacing and control. All lines are fully buffered to TTL (Transistor-Transistor Logic) (5V) level. Examples of input signals are alarm state, paper low and interlocks. Examples of output signals are coin light and alarm reset. All output control lines are taken via a buffer and can sink/source 200mA. A suitable external buffer device would be required to control larger currents.

With reference to Figure 2 a software architecture 20 according to the present invention is shown schematically. A serial port driver 21 connects to serial ports 22. The operating system layer 23 contains sockets 24, which are interfaced via a software protocol to a socket server layer 25. The serial event handlers are a module 26 in the socket server layer. This provides an advantage over the prior art where serial event handlers are written in the firmware of a microcontroller unit in a serial port expansion module

along with several costly UARTs. Finally, the application layer 27 is on top of the socket server layer.

In order to provide system integrators with a simple means of controlling peripherals, the socket server layer is provided as a run-time device manager based on a Windows™ sockets interface. An additional ActiveX™ component is also provided which, when combined with the socket server layer allows device control directly from HTML (HyperText Markup Language) and Java™ script. This considerably reduces the complexity of application development, allowing simple scripting to be used to control all devices.

With reference to Figure 3 there is a PC 30 containing a controller module according to the present invention connected by a ribbon cable 31 (from the connector 13 of Figure 1) to a peripheral interface module 32. This Figure demonstrates how the controller module can be used to embed a PC in a kiosk application. A large number of peripherals 33 are connected to the PC using its own ports, the ports of the controller module and through the connectors of the peripheral interface module.

The motherboard is a standard micro-ATX (Advanced Technology eXtended) form factor PC mainboard. Compared to standard ATX, it enables smaller, cost-reduced system designs. For example, the mainboard square area is reduced to approx. 92 square inches. It typically contains integrated graphics and audio, 2 DIMMs (Dual In line Memory Modules) and a maximum of 3 PCI slots.

With reference to Figure 4 there is a power supply 40 for embedding within the kiosk environment. The control module contains a connection 41 to a battery management circuit 42. The UPS 43 is a BiUPS® (Built-In UPS) from Magnum Power Solutions Limited, which has output control signals 44, a NiCd back-up battery 45 and an AC (alternating current) input 46. It provides the host computer system power distribution board 47 with embedded un-interruptible protection of the UPS power output 48. It occupies the same mechanical outline as an internal switched-mode power supply.

The degree of protection depends on the capacity of the back-up battery. The standard BiUPS system has two states for the charging of the back-up battery: fast and trickle charge. The problem with this is that the NiCd battery is not optimally conditioned. In this embodiment, the system is improved by diverting the electrical connection 49 of the NiCd battery to the BiUPS power supply through a battery management circuit that is controlled by the microcontroller. This battery management function, combined with the other power supply control signals between the power supply and the microcontroller, allow the monitoring and control of the optimum charging conditions of the back-up battery.

Further modifications and improvements may be added without departing from the scope of the invention herein described

CLAIMS

1. A control module comprising:
   a motherboard bus connector for communication with a motherboard;
   a motherboard bus to serial port bridge module;
   at least one serial port connector; and
   a processor module.

2. The control module of Claim 1 adapted to provide at least one peripheral control port for said motherboard.

3. The control module of any previous Claim wherein the processor module comprises a monitoring means for monitoring the state of said motherboard.

4. The control module of Claim 3 wherein the monitoring means further monitors the state of software running on said motherboard.

5. The control module of any previous Claim wherein the processor module has a battery power supply separate from the PC power supply.

6. The control module of any previous Claim wherein the processor module further comprises a power supply monitoring means for monitoring the state of a power supply supplying said motherboard.

7. A system comprising a motherboard and the control module of any previous Claim.

8. The system of Claim 7 further comprising a socket server means for providing event handlers for at least one serial port corresponding to said at least one serial port connector and operating substantially in between the application layer and the operating system layer of the software executing on the motherboard.

9. The system of Claim 7 further comprising a socket server means for providing event handlers for said at least one peripheral control port and operating substantially in between the application layer and the operating system layer of the software executing on the motherboard.

10. The system of any previous Claim further comprising a battery, a power supply and a battery management circuit wherein an electrical connection between said battery and said power supply is diverted through said battery management circuit and said battery management circuit is controlled by said processor module.


Tri LED
13
Alarm
114
COM3
COM2
COM1
Reset
12C
Alarm Out
Interlock
DIO (16 Lines)
COM3
COM4
COM5
RS232 Trans.
14
15
-12-
Local Bus
Serial Interface
-16-
-17-
-18-
M/B Reset
M/B On
-116-
27
Speaker Out
Line In
113
-112-
11
6 Way Header
117
10
111
20 Way Header
-110-
1 Wire Serial
1 wire serial
PSU On
AC Fail
Shutdown
+5V Batt
Buffers
EEPROM and RTC or iBUTTON
19
115
Battery 3.6V 80mAH
Spare IO
LCD HEADER

FIG.1


20
Application
27
Socket Server
25
26
24
Operating System
23
21
PCI RS232
COM3
COM4
22

FIG. 2


33
(25)
12V
STEREO AMPLIFIER 20W rms
(22)
(17)
(23)
TRACKER-BALL
S S S S P IEC AC DIST'N
(24)
LINE OUT
MIC
LINE IN
PS/2
AC
USB 1 2
VGA
COM 1
COM 2
MIDI
LPT 1
AGP CARD
COM 3
COM 4
COM 5
DIO
PCI 1
ePC500-IB01
ISDN
PCI 2
LAN
30
(21)
31
(19)
(20)
CARD READER
12V
24V
TOUCHSCREEN CONTROLLER
12V
PRINTER ePPM-01
PAPER LOW SENSOR
37 WAY RIBBON
PC CONTROLLED
S S S S P IEC AC DIST'N
33
CRT
240V AC
(18)
32
(8)
(9)
(10)
(11)
(12)
(13)
(14)
DIO
COM3
COIN CCTALK
HOPPER
CH4
TKIM-IB01
COM 5
PL
DC1
DC2
AC2
AC1
IL1
IL2
DIB
IN-LINE FILTER
(15)
(16)
(17)
ISDN
LAN
LINE IN
AC IN
REAR PANEL
(1)
(2)
(3)
(4)
(5)
(6)
(7)
COIN MECH
COIN HOPPER
NOTE READER
I/LOCK SWITCH 1
I/LOCK SWITCH 2
DALLAS iBUTTON
METER
33

Fig. 3


Ni-Cad Battery
45
41
20 Way Header
49
Battery Management
42
46
44
PSU Cntrl
Power Dist. Board
Magnum 1072 Power Supply
-43-
48
M/B Power
-47-
40

FIG. 4

This Page is Inserted by IFW Indexing and Scanning Operations and is not part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☑ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.
As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.